

JAMMA SYSTEM - INTERFACE CONNECTOR

<i>Function</i>	<i>Pins</i>	<i>Function</i>	<i>Wire Colour</i>
GND	A 1	GND	<i>GREY</i>
GND	B 2	GND	
+5 V	C 3	+5 V	<i>YELLOW</i>
+5 V	D 4	+5 V	
-5 V	E 5	-5 V	<i>GREEN / BROWN</i>
+12 V	F 6	+12 V	<i>BLUE / YELLOW</i>
	G 7		
COIN COUNTER 2	H 8	COIN COUNTER 1	<i>WHITE / BLUE</i>
	I 9		
SPEAKER (-)	J 10	SPEAKER (+)	<i>BLACK / BLUE</i>
	K 11		
VIDEO GREEN	L 12	VIDEO RED	<i>RED</i>
VIDEO SYNC	M 13	VIDEO BLUE	<i>BLUE</i>
SERVICE	N 14	VIDEO GND	<i>BLACK</i>
	O 15	TEST	
COIN SWITCH 2	P 16	COIN SWITCH 1	<i>GREEN / ORANGE</i>
START SWITCH 2	Q 17	START SWITCH 1	<i>WHITE / ORANGE</i>
2P CONTROL UP	R 18	1P CONTROL UP	<i>GREEN / BROWN</i>
2P CONTROL DOWN	S 19	1P CONTROL DOWN	<i>PURPLE / GREEN</i>
2P CONTROL LEFT	T 20	1P CONTROL LEFT	<i>PURPLE / BLUE</i>
2P CONTROL RIGHT	U 21	1P CONTROL RIGHT	<i>GREEN / BLACK</i>
2P FIRE 1	V 22	1P FIRE 1	<i>ORANGE / BLACK</i>
2P FIRE 2	W 23	1P FIRE 2	<i>RED / YELLOW</i>
2P FIRE 3	X 24	1P FIRE 3	<i>GREEN / RED</i>
	Y 25		
	Z 26		
GND	27	GND	<i>GREY</i>
GND	28	GND	